

KS8000 WIRELESS ALARM SYSTEM

8 Zone Wireless Panel

Wireless Sensors

Voice Dialer

A flexible and fully featured professional 868MHz wireless alarm system providing a solution to both domestic and light industrial applications. Minimal panel programming required, simple learning of wireless sensors, extremely easy to use and operate.



Features:

8 Zones + Additional Wireless PA

Zones programmable as one of 5 types: Immediate, Timed, Intermediate or 24H/Fire

Hard Wired Zone input (Z2)

Simple Zone by Zone "Self Learn" of all Transmitters

All Wireless Zones send a Low Battery and Tamper signal

4 Different User Codes, 1 Installer Code

2 separate Dialler Outputs for connection to AD-01 Dialler

Arm/Disarm using Keypad, Key fob or Key switch

Zone Bypass: All zones can be temporarily bypassed

All Zones can be programmed On/Off as Door Chime

Walk Test Mode: Simple wireless sensor placement test

Switched 12V Output: Active when Panel is in Full Guard

Programmable On/Off Anti-Jam Detection

Double Knock programmable On/Off for each zone

Cross Zone Detection programmable On/Off (2 different zones must be activated before an alarm occurs)

5 Event Memory

Built-in Speaker plus Output for 2 additional 16 Ohm Spkrs

SAB and Strobe Outputs



Remote Control

- 70 x 40 x 12 mm
- Part/Full Guard, plus Off and Panic Buttons
- Low Battery Indication
- 12V Lithium Battery



Wireless PIR Sensor

- 105 x 60 x 35 mm
- 9M Coverage
- Pulse Count (1/3/5)
- Power Save Mode
- 2 x AA Batteries



Wireless Contact

- 85 x 35 x 25 mm
- Magnet Included
- Terminal inside for add-on sensor
- 3V Lithium Battery



Wireless Smoke

- 140 x 40 mm
- Batteries included

Product No	Description
KS8000	8 Zone Wireless Control Panel
HTX008/4	4 Button Remote Control
HPIR008	Wireless PIR Detector
HWM008	Wireless Door/Window Contact
HSD008	Wireless Smoke Detector
AD-01	Voice Dialler